

Key Features

- Supports Auto-Tracking and Audio Transmission
- Working with AREC Media Station, AM-600 Can Become a Microphone to Record the Presenter's Voice
- Easy Control of Start/Stop Tracking and Mute Functions by Built-in Buttons
- Built-in Rechargeable Lithium Battery
- Accurate Tracking Performance even if the Lecturers Turn Their Back to the Tracking Camera to Write on the Board

- 1 Ø3.5 audio input jack
- 2 Power / tracking on-off
- 3 Microphone pairing / mute
- 4 Power input USB Micro-B port

Specification

AREC TP-100

AM-600	
Tracking and Indicators	
Effective Distance (tracking and audio)	3~12m radius
Upper Indicators	Power on-off / tracking start-pause
Lower Indicators	Wireless pairing / mute
Audio	
Audio Input	Ф3.5mm phone jack
	Built-in Microphone
General	
Power Supply	Built-in rechargeable lithium battery, 3.7V, 720mA Interface: USB Micro-B
Temperature	0~50°C
Battery Life	4hrs, after fully charged
Dimension	83(L) x 41.5(W) x 18.15(H)mm
Weight	67g



AREC Inc. | www.arec.com | sales@arec.com

Headquarters: Taipei, Taiwan Address: 3F, No. 367, Sec.2, Wenhua RD., Banqiao Dist., New Taipei City 220, Taiwan (R.O.C) TEL: +886-2-8259-5060